date 09/11/2024 **page** 1 of 3

MODEL: CLS0301 | DESCRIPTION: SPEAKER

FEATURES

- 30 mm
- round frame
- 1.0 W
- •8Ω
- neodymium magnet

same sky

• paper cone



.....

RoHS

SPECIFICATIONS


.....


parameter	conditions/description	min	typ	max	units
input power			1.0	2.0	W
impedance	at 1.0 kHz, 1.0 V	6.8	8	9.2	Ω
resonant frequency (Fo)	at 1.0 V	344	430	516	Hz
frequency response		Fo		20,000	Hz
sound pressure level	at 1.0 W, 50 cm, avg. at 0.6, 0.8, 1.0, 1.2 kHz	81	84	87	dB
buzz, rattle, etc.	must be normal at sine wave			2.83	V
dimensions	Ø30 x 5.3				mm
magnet	Nd-Fe-B				
cone material	paper				
terminal	solder pads				
weight			5.8		g
operating temperature		-25		70	°C
hand soldering	for maximum 3 seconds	340	350	360	°C
RoHS	yes				

Notes: 1. All specifications measured at 15~35°C, humidity at 25~75%, under 86~106 kPa pressure, unless otherwise noted.

MECHANICAL DRAWING


units: mm tolerance: ±0.2 mm





FREQUENCY RESPONSE CURVE

parameter	conditions/description	
potentiometer range	50 dB	
rectifier	RMS	
lower limit frequency	20 Hz	
wr. speed	100 mm/sec	
zero level	60 dB	



REVISION HISTORY

rev.	description	date
1.0	initial release	07/03/2007
1.01	brand update	02/27/2020
1.02	logo, datasheet style update	08/05/2022
1.03	CUI Devices rebranded to Same Sky	09/11/2024

The revision history provided is for informational purposes only and is believed to be accurate.

Same Sky offers a one (1) year limited warranty. Complete warranty information is listed on our website.

same sky

Same Sky reserves the right to make changes to the product at any time without notice. Information provided by Same Sky is believed to be accurate and reliable. However, no responsibility is assumed by Same Sky for its use, nor for any infringements of patents or other rights of third parties which may result from its use.

Same Sky products are not authorized or warranted for use as critical components in equipment that requires an extremely high level of reliability. A critical component is any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.